

# DATA SHEET

# ESYLUX

## MD 200 black

### Item number

EM10025334

### GTIN

4015120025334



### Technical data

#### GENERAL

Device category	Outdoor motion detector
Product information	Please note the Explanation of circuit breaker in the download area of the product! Intense sunlight over a longer period of time can change the color tone.
User interface	Adjusting controller
Remote controllable	-
Conformity	CE, EAC, RoHS, WEEE
Warranty	5 years

#### ATTACHMENT

Installation type	Surface mounting
Installation position	Wall
Type of connection	Push terminal
Connectable wire cross section	1.5 - 2.5 mm <sup>2</sup>

#### HOUSING

Dimensions	Length 102 mm x Width 74 mm x Height/Depth 81 mm
Weight	196 g
Material	UV-stabilised polycarbonate
Protection type	IP44
Permissible ambient temperature	-25 °C...+55 °C
Relative humidity	5 - 95 %, non-condensing
Colour	black, similar to RAL 9005

#### ELECTRICAL VERSION

Control system	ON/OFF
Protection class	II
Nominal voltage	230 V ~ / 50 Hz

Ø 20 m	200°	ON/OFF	IP44	1 CH	
--------	------	--------	------	------	--

### Product description

- Motion detector with **200° field of detection** for convenient light switching
- Sensing and range adjustment due to revolving and tilting spherical head technology
- Special bracket for mounting on inner and outer corners, available as accessory

### Offers special product features like:

- One-hand plug-in base
- Zero-cross switching

In-rush current	30 A / 20 ms
Power consumption	0.5 W

#### SENSORS

Detection angle	200° sensor horizontally rotatable +/- 90°
Detection range diagonally	Ø 20 m
Detection range head-on	Ø 10 m
Field of detection	up to 175 m <sup>2</sup>
Range adjustment	mechanically by tilting the motion detector head max 60°
Recommended installation height	2.5 m
Max. mounting height	2.5 m
Light measurement	mixed light
Level of brightness	10 - 2000 lx

#### CHANNELS (LIGHTING / HVAC)

Number of light channels	1
Push button input HVAC	-
Number of parallel switchable detectors	8
Slave input	-
Switching delay from "dark to light"	0 s
Switching delay from "light to dark"	0 s
Constant light control	-
Channel	<b>C1</b> Lighting
Function	Switching
Switching capacity	230 V/50 Hz 1000 W/4,5 A (cos phi = 1) 500 VA/2,25 A (cos phi = 0,5) 250 W LED
Switch contact	make contact / non-floating

## MD 200 black

### Item number

EM10025334

### GTIN

4015120025334

Push button input	-
Impulse mode	-

Switch-off delay time	10 s...15 min (adjustable in steps)
-----------------------	-------------------------------------



### Factory settings

GENERAL	
Sensitivity	100 %

CHANNELS (LIGHTING / HVAC)	
Channel	C1 Lighting
Operating mode	fully automatic

### Accessories

Product designation	Item number	Product description	GTIN
<b>Electrical accessories</b>			
FILTER 230 V	EP10426988	Filter for suppression of inductive loads, such as relays, contactors, fluorescent lamps and transformers	4015120426988
<b>Mounting</b>			
MD EDGE MOUNTING BK	EM10025532	Corner bracket for MD series, black	4015120025532

Dimension drawing	Field of detections	Detection range	
		<div>■ Diagonally (A)</div>	Ø 20 m
		<div>■ Frontal (B)</div>	Ø 10 m

## MD 200 black


### Item number

EM10025334

### GTIN


4015120025334

### Circuit diagram




Standard operation with optional parallel wiring of max. eight motion detectors.

### Circuit diagram



When connecting inductors (e.g. relays, contactors, ballasts) the use of a filter (A) may be necessary.

### Circuit diagram



Standard operation with automatic stairwell light.

### Detailed product description

- Motion detector with **200° field of detection** for convenient light switching
- One-handed plug-base installation for quick and easy installation
- Double diaphragm line entry
- Connector bracket with large wiring space and optional line entrance from the top, bottom or rear
- Plug-in terminal for through-wiring of the protective conductor included
- Sensing and range adjustment due to revolving and tilting spherical head technology
- Zero-cross switching: Extension of the lifetime of relays and illuminants with electronic ballasts (e.g. fluorescent lamps, LEDs) thanks to more gentle zero-cross switching
- For wall mounting
- Special bracket for mounting on inner and outer corners, available as accessory